

Technische Daten | Technical data | Caractéristiques techniques

Communication:	NFC – Near Field Communication Mifare DESFire® EV2 ISO14443-A (13,56MHz)
Power supply:	Batteries: 3 × Alkaline (LR03) AAA Voltage 3 × 1,5 V = 4,5 V
Battery life:	Up to 1 year
Radio range:	Communication with the control unit - up to 75 m
KeyCard range:	Up to 35 mm to the NFC module
Radio frequency:	868,35 MHz
Compatibility:	WiPro III WiPro III safe.lock WiPro easy C.A.S. III
Operating temperature:	-10° C bis +70° C
Dimensions (Ø × D):	89 × 19,5 mm
Weight:	100 g
Scope of deliver:	NFC Modul KeyCard Adhesive pad 3 × Alkaline (LR03) AAA Batteries



Thitronik GmbH hereby declares that this product complies with the requirements and regulations of the directive 2014/53/EU. The full declaration of conformity is available for download: <https://www.thitronik.de/support>

The NFC module may only be used for wireless control of the THITRONIK alarm system. Any other use, in particular use for other technical applications, is prohibited and may result in damage to the product and danger to persons and property. The manufacturer accepts no liability for damage caused by improper use of the NFC module.



FR
Cet appareil
et sa batterie
se recyclent

À DÉPOSER
EN MAGASIN



ou

À DÉPOSER
EN DÉCHÈTERIE



Points de collecte sur www.quefairedemesdechets.fr

THITRONIK® NFC Modul

Kurzanleitung | Quick start Guide | Instructions brèves



Langenleitung
Long instructions
Instructions longues



Thitronik GmbH | Finkenweg 9 – 15 · 24340 Eckernförde
kontakt@thitronik.de | www.thitronik.de

Inbetriebnahme | Commissioning | Mise en service

1. Batteriesicherung entfernen

EN: Remove battery strap

FR : retirer la languette de protection de la batterie



2. Anlernmodus der Alarmzentrale starten

EN: Start the teach mode of the alarm control panel

FR : démarrer le mode d'appairage de la centrale d'alarme



3. NFC Modul mit beiliegender Karte auslösen

EN: Trigger NFC module with enclosed card

FR : activer le module NFC avec la carte jointe



4. Anlernmodus der Alarmzentrale beenden (Siehe Anleitung aus Schritt 2.)

EN: Exit the teach mode of the alarm control panel (See manual from step 2.)

FR : quitter le mode d'appairage de la centrale d'alarme (voir instruction de l'étape 2)



5. Schutzfilm von Klebefläche entfernen

EN: Remove the protective film from the adhesive surfaces

FR : décoller le film de protection des autocollants



6. Geeignete Stelle im Fahrzeug finden, Oberfläche reinigen und NFC Modul ankleben

EN: Find a suitable place in the vehicle, clean the surface and stick on the NFC module.

FR : choisir l'emplacement du module NFC, nettoyer la surface avant l'application et le coller



Weitere NFC-Tags anlernen | Teaching additional NFC tags | Apprendre d'autres tags NFC

1. Zum Öffnen drehen

EN: Turn to open

FR : tourner pour ouvrir



2. Anlernmodus des NFC Moduls starten

EN: Start teach mode of the NFC module

FR : lancer le mode d'appairage du module NFC

3. NFC-Tag an Modul halten

EN: Hold NFC tag on module

FR : tenir le tag NFC sur le module



4. Anlernmodus beenden

EN: Exit teach mode

FR : quitter le mode d'appairage